

Display LCD LCD Display



CORNICE - Argento / Oro.
FRAME - Chrome / Gold.



COLORI / COLOURS

Bianco, giallo, acquamarina, rosso
e verde. / White, yellow, aquamarine,
red and green.




Icaro blu con icone /
Blue Icaro with
alarm signals

Icaro nero con icone /
Black Icaro with
alarm signals



DIMENSIONI / DIMENSIONS



ICARO

Display lcd di piano.
Landing lcd position indicator.




FUNZIONI PRINCIPALI


- Colori: illuminazione bianca su fondo blu oppure 5 colori a scelta (azzurro, bianco, ambra, verde, rosso) su sfondo nero.
- Segnali: piano, frecce, fuori servizio, allarme inviato e sovraccarico (OPZIONALI).
- Programmazione facile tramite apposito tastierino EASY incorporato.
- Minigong tritonale e programmabile.
- 32 fermate in binario, 11 fermate 1 polo per piano, 64 fermate in modalità autonoma (sensori magnetici).
- Comunicazione: seriale Vega, CAN, RS485, parallela.
- Possibilità di programmare la codifica binaria, binaria negata, BCD, Gray e 7 segmenti.
- Montaggio rapido: frontale tramite cornice o a filo piastra con perni saldati su piastre piane da 1.2 e 2mm.
- Cablaggio: a vite o connettori precablati (AMP o JST).
- Comune: positivo o negativo (selezionabile).
- Alimentazione: 12/24Vdc +/- 10%.

MAIN FEATURES

- Colours: white LED on blue background or 5 different colours (navy blue, white, yellow, green and red) on black background.
- Signals: floors, arrows, out of service, sent and acknowledged alarms (yellow and green) and overload red signal
- Easy programming by a dedicated integrated keyboard.
- Integrated and programmable three-tone chime.
- 32 stops in binary code, 11 stops 1 wire for floor, 64 stops in independent mode (magnetic sensors).
- Communication: parallel, Vega serial, CAN and RS485.
- Possibility to set binary, inverted binary, BCD, Gray, 7 segments codes and magnetic sensors.
- Fast Fixing: frontal mounting with frame or flush mounting on 1.2 and 2mm faceplates through soldered studs.
- Wiring: screws or pre-wired connectors (AMP or JST).
- Common: positive or negative (selectable on-board option).
- Power supply: 12/24Vdc +/- 10%.



Scasso per
montaggio
con cornice
/ Cut out for
mounting with
frame



Scasso per
montaggio
a filo / Cut
out for flush
mounting

Ingombro della scheda montata dietro la piastra. / Display Encumbrance.
Dimensioni in mm / Dimensions in mm.